RFID long range reader



Model:JTPR-2

Notice: re-power again after setting be finished

Product Introduction

JTPR-2 RFID long range reader adopts 2.4GHZ freefrequency wireless communication technologies with high sensitivity, low power consumption, no harm to human body, stable function, lightning protection, high waterproofing grade, high capacity of resisting disturbance& high data transmission speed, can compatible with multi-type card reading device, which be widely used in RFID access control system, RFID parking management system, personnel location system, products tracking system, army, Prison, family-school system, etc.

Technology parameter

| Power supply | DC12V |
|---------------------------|-------------------------------|
| Work current | ≤110mA |
| Work frequency | 2.4GHz∼2. 483GHz |
| Operating temp | -20℃~+85℃ |
| Relative humidity | ≤90% |
| Read distance | 1m~80m (Nonlinear adjustable) |
| Receiving sensitivity | -90dBm |
| Anti-collision capacity | 100pcs |
| Copper core load capacity | 1. 36A |

Function Introduction

- → Orientation Identification Orientation Identification work scope is less than 180 degree;
- ★Reading range can be adjustable Integrating with digital attenuator system for control reader reading range, which can solve customer's reading range requirement in the real application.;
- → High security of resisting disturbance Adopts frequency hopping& multiple-address technology, Strong encryption to card info by the unique program encryption technology, Data transmitting to reader after multi-type checking way for data processing;
- ★ Anti-collision 100 pcs RFID tag numbers can be read simultaneously:
- ★ Low frequency activation With 125K low frequency activation function, which can the control reading range effectively;
- → Interregional delay function Identify entrance & exit address group, false operation caused by tag when the entrance & exit is very close to adjacent;
- → Multi-type data output format

 With Wigand, RS485 data format output.

Add: Mingjinhai Industry Park, Tangtou Road, shiyan Town, Bao' an District Shenzhen, Guangdong Province, 1-2F Tel: (86)755-2957 3855 Fax: (86)755-2957 3955 Web: www.jutairfid.com E-mail: info@jutairfid.com